

XCANLED Installation Manual

General Location | DC Voltage



Webpage



APPLICATION

The XCANLEDDC luminaire is an industrial-grade product suitable for harsh and general locations. Installation areas include indoor, outdoor, and wet locations. Frequent exposure to moisture, dirt, corrosion, vibration, and rough usage is common for this product family. As defined by the National Electrical Code (NEC) and the Canadian Electrical Code (CEC), they are suitable for use in the following areas:

| | |
|---------------------|---|
| Certified to: | CSA 22.2 No. 250.0, Conforms To UL 1598 Standard |
| Housing: | Copper-free 6061-T6 aluminium & acrylic lens |
| Mounting: | Two (2) 1/4-20 screws or bolts |
| Voltage: | VDC: 12-24VDC |
| Current (Max): | 2.64A@12VDC 1.4A@24VDC |
| Connections: | 6' Flying Lead Black: Line White: Neutral Green: Ground |
| Temperature Range: | -40° C to +75° C |
| Ingress Protection: | IP66 |



WARNING

To avoid the risk of fire, explosion, or electric shock, this product should be installed, inspected, and maintained by a qualified electrician only, in accordance with all applicable electrical codes.



WARNING

To avoid electric shock:

- Be certain electrical power is OFF before and during installation and maintenance.
- Luminaire must be connected to a wiring system with an equipment-grounding conductor.

INSTALLATION STEPS

STEP 1:

Inspect shipping package and contents to ensure no damage has occurred during shipping.

STEP 2:

Loosen each bracket 1/4-20 yoke hex bolt (2x) slightly to allow some free movement. Be sure not to loosen too much that they disengage from the XCANLEDDC body. This will allow for easier installation and aiming.

STEP 3:

Mount fixture to desired location with 2x 1/4-20 screws or bolts.

*See mounting dimensions for installations with fixed studs if desired.

STEP 4:

Adjust fixture to desired angle and tighten bracket 1/4-20 yoke bolts.

STEP 5:


Connect fixture flying lead to 12 or 24 VDC power supply (VDC Models) in accordance with all applicable electrical codes.



Black: DC - | White: +12-24 VDC

STEP 6:

Energize fixture.



MOUNTING DIMENSIONS

